

# EQUIPMENT COMPATIBILITY CHART (PAL/SECAM)

## GENERAL COMPATIBILITY INFORMATION

FV CONTROLLER SERIES	INSTALLED TRANSPORT CONTROL DRIVERS	RS-232C DRIVER TYPES
MEDIA COMMANDER 100	RS-422A, RS-232C, Panasonic Control-M (5-pin), Sony Control-L (LANC)	<b>R5</b> (JVC), <b>R6</b> (Panasonic), <b>R8</b> (Sony)
MEDIA COMMANDER 200	RS-422A, RS-232C, Panasonic Control-M (5-pin), Sony Control-L (LANC)	<b>R5</b> (JVC), <b>R6</b> (Panasonic), <b>R8</b> (Sony)
V-STATION 3300	RS-422A, RS-232C, Panasonic Control-M (5-pin), Sony Control-L (LANC)	<b>R5</b> (JVC), <b>R6</b> (Panasonic), <b>R8</b> (Sony)

### APPLICATION NOTES FOR GENERAL COMPATIBILITY

Device Code & Driver Type initialize controller to match transport characteristics. The appropriate Driver will be automatically selected when the FV Control Cable is plugged into the controller—except as noted below in the Device Driver column. All VCRs & camcorders must have a linear time display (not a 4-digit reel counter) & a shuttle lock mode.

## VCRs

MFR	MODEL NUMBER	TAPE FORMAT	CONTROL PROTOCOL	FV CONTROL CABLE	FV CONTROLLER SERIES	DEVICE CODE/DRIVER
Blaupunkt	RTV-915, 920, 925	SVHS	Control-M	FV0050P	100, 200, 3300	4
Blaupunkt	RTV-926	SVHS	Control-M	FV0050P	100, 200, 3300	5
Blaupunkt	RTV-950, 966	SVHS	Control-M	FV0050P	100, 200, 3300	5
Blaupunkt	RTV-1000	SVHS	Control-M	FV0050P	100, 200, 3300	5
JVC	BR-D50, D51****	Digital-S	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-D80, D85	Digital-S	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-D350****, D750	Digital-S	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-S500***	SVHS	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-S500^^	SVHS	RS-232C	FV0075	100, 200, 3300	3 R5
JVC	BR-S522, S525	SVHS	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-S605**	SVHS	RS-232C	FV0075	100, 200, 3300	1 R5
JVC	BR-S605B***	SVHS	RS-232C	FV0075	100, 200, 3300	2 R5
JVC	BR-S622	SVHS	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-S800***	SVHS	RS-422A	FV0077	100, 200, 3300	3
JVC	BR-S800^^	SVHS	RS-232C	FV0075	100, 200, 3300	3 R5
JVC	BR-S822	SVHS	RS-422A	FV0077	100, 200, 3300	3
JVC	SR-S388	SVHS	RS-232C	FV0075	100, 200, 3300	4 R5
Panasonic	AG-4700	SVHS	Control-M	FV0050P	100, 200, 3300	6
Panasonic	AG-5700	SVHS	RS-232C	FV0074	100, 200, 3300	1 R6
Panasonic	AG-7600^, 7700	SVHS	RS-422A	FV0077	100, 200, 3300	2
Panasonic	AG-7650^, 7750	SVHS	RS-422A	FV0077	100, 200, 3300	2
Panasonic	AJ-D230^	DVCPRO	RS-232C	FV0074	100, 200, 3300	2 R6
Panasonic	AJ-D640^, D650	DVCPRO	RS-422A	FV0074	100, 200, 3300	2
Panasonic	AJ-D750	DVCPRO	RS-422A	FV0077	100, 200, 3300	2
Panasonic	AU series (selected)	MII	RS-422A	FV0077	100, 200, 3300	4
Panasonic	NV-FS88, FS90	SVHS	Control-M	FV0050P	100, 200, 3300	4
Panasonic	NV-FS100	SVHS	Control-M	FV0050P	100, 200, 3300	4
Panasonic	NV-FS200	SVHS	Control-M	FV0050P	100, 200, 3300	5
Panasonic	NV-HS900	SVHS	Control-M	FV0050P	100, 200, 3300	6
Panasonic	NV-HS1000****	SVHS	Control-M	FV0050P	100, 200, 3300	6
Sanyo	GVR-S960	SVHS	RS-422A	FV0077	100, 200, 3300	1
Sony	BVU series (selected)	U-Matic	RS-422A	FV0077	100, 200, 3300	4
Sony	BVW series (selected)	Betacam SP	RS-422A	FV0077	100, 200, 3300	4
Sony	EV-C2000*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	EV-S9000*	Hi8	Control-L (5-pin)	FV0049	100, 200, 3300	4
Sony	EVC-500	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	3
Sony	EVO-9650	Hi8	RS-232C	FV0079	100, 200, 3300	2 R8
Sony	EVO-9720	Hi8 (Dual)	RS-232C	FV0079	100, 200, 3300	3 R8
Sony	EVO-9800A, 9850	Hi8	RS-422A	FV0077	100, 200, 3300	4
Sony	DHR-1000	Mini DV/DV CAM	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	DSR-30	Mini DV/DV CAM	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	PVW series (selected)	Betacam SP	RS-422A	FV0077	100, 200, 3300	4
Sony	SLV-E90	SVHS	Control-L (2.5mm)	FV0051	100, 200, 3300	3
Sony	SVO-5800	SVHS	RS-422A	FV0077	100, 200, 3300	3
Sony	SVO-9600	SVHS	RS-422A	FV0077	100, 200, 3300	3
Sony	SVP-5600^	SVHS	RS-422A	FV0077	100, 200, 3300	3
Sony	SVP-9000^	SVHS	RS-422A	FV0077	100, 200, 3300	3
Sony	UVW-1600^, 1800	Betacam SP	RS-422A	FV0077	100, 200, 3300	4
Sony	VO series (selected)	U-Matic	RS-422A	FV0077	100, 200, 3300	4

### APPLICATION NOTES FOR VCRs

\* Hi8 RC Time Code (RCTC)    \*\* Requires JVC SA-K17 RS-232C Serial Interface Board    \*\*\* Requires JVC SA-K26 RS-422A Serial Interface Board  
 \*\*\*\* Requires JVC SA-K28 RS-232C Serial Interface Board    ^ Source only    ^^ Requires JVC SA-K37 RS-232C Serial Interface Board

## CAMCORDERs

<b>MFR</b>	<b>MODEL NUMBER</b>	<b>TAPE FORMAT</b>	<b>CONTROL PROTOCOL</b>	<b>FV CONTROL CABLE</b>	<b>FV CONTROLLER SERIES</b>	<b>DEVICE CODE</b>
Blaupunkt	CCR-894	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Blaupunkt	FV-895*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Blaupunkt	DC 196**	Mini DV	Control-M	FV0050P	100, 200, 3300	3
Canon	EX2Hi*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Canon	UC-X30Hi*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Panasonic	NV-DX1**	Mini DV	Control-M	FV0050P	100, 200, 3300	3
Sony	CCD-TR3E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-TR2000E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-TR3000E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-TR3300E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-TRV100E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-V800*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-V6000*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	CCD-VX1E*	Hi8	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	DCR-VX700**	Mini DV	Control-L (2.5mm)	FV0051	100, 200, 3300	4
Sony	DCR-VX1000**	Mini DV	Control-L (2.5mm)	FV0051	100, 200, 3300	4

#### **APPLICATION NOTES FOR CAMCORDERS**

\* Hi8 RC Time Code (RCTC) \*\* Source only

### **MODULAR DIGITAL MULTI-TRACK RECORDERS**

<b>MFR</b>	<b>MODEL NUMBER</b>	<b>TAPE FORMAT</b>	<b>CONTROL PROTOCOL</b>	<b>FV CONTROL CABLE</b>	<b>FV CONTROLLER SERIES</b>	<b>DEVICE CODE</b>
Fostex	D-30	DAT	RS-422A	FV0077	100, 200	5
Fostex	RD-8	ADAT (SVHS)	RS-422A	FV0077	100, 200	11
Sony	PCM-800*	DTRS (Hi8)	RS-422A	FV0077	100, 200	12
Tascam	DA-88**	DTRS (Hi8)	RS-422A	FV0077	100, 200	12

#### **APPLICATION NOTES FOR MDMs**

\* Requires Sony DABK-801 Interface Board \*\* Requires Tascam SY-88 Interface Board

### **LASER DISK PLAYERS**

<b>MFR</b>	<b>MODEL NUMBER</b>	<b>TAPE FORMAT</b>	<b>CONTROL PROTOCOL</b>	<b>FV CONTROL CABLE</b>	<b>FV CONTROLLER SERIES</b>	<b>DEVICE CODE/DRIVER</b>
Sony	LDP-1200, 1450	Laservision	RS-232C	FV0079	100, 200, 3300	1 R8
Sony	LDP-1500, 1550	Laservision	RS-232C	FV0079	100, 200, 3300	1 R8
Sony	LDP-2000, 3600	Laservision	RS-232C	FV0079	100, 200, 3300	1 R8
Sony	MDP-1100, 1150	Laservision & CD	RS-232C	FV0079	100, 200, 3300	1 R8
Sony	MDP-1700	Laservision & CD	RS-232C	FV0079	100, 200, 3300	1 R8

### **VIDEO MIXERS, SEGs, & TITLERS**

<b>MFR</b>	<b>MODEL NUMBER</b>	<b>TRIGGER TYPE</b>	<b>CONTROL PROTOCOL</b>	<b>FV CONTROL CABLES</b>	<b>FV CONTROLLER SERIES</b>
Panasonic	WJ-AVE55	GPI	RS-232C Serial	FV0053, FV0089	3300 VX, 3300 PLUS
Panasonic	WJ-MX20	GPI	RS-422A Serial	FV0053, FV0063	3300 PLUS
Panasonic	WJ-MX30	GPI	RS-232C Serial	FV0053, FV0088	3300 PLUS
Panasonic	WJ-MX50	GPI	RS-232C Serial	FV0053, FV0088	3300 PLUS
Pinnacle	GeniePlus	GPI	On/Off	FV0053	3300, 3300 VX, 3300 PLUS
Sony	XV-D1000	GPI	On/Off	FV0053	3300, 3300 VX, 3300 PLUS
Videonics	MX-1/MX-PRO	GPI	TTL Serial	FV0087	3300 VX, 3300 PLUS
Videonics	TM-2000, 3000	GPI	On/Off	FV0087	3300, 3300 VX, 3300 PLUS

FutureVideo, Media Commander, V-Station, and EditLink are registered trademarks of FutureVideo Products, Inc. Manufacturer's names, product names, and model numbers used herein are trademarks of their respective owners. Compatibility, specifications, and availability subject to change without notice. ©1997-99 FutureVideo Products, Inc. All rights reserved. 60-02-0037

**FutureVideo Products, Inc P.O. Box 6251 Laguna Niguel, CA USA 92607-6251 (949) 363-1286 [www.futurevideo.com](http://www.futurevideo.com)**